

# Online Tracking Guide

## A. Register a Tracking account

- ✚ First login the Tracking system: <http://whereaboutz.net/>



- ✚ Click "Sign Up" into the register, and finally click "Apply", we will send you a E-mail which contains account information.



Attention: Select "Account" to login with E-mail; "IMEI" login with one single device, and "IMEI" option' s password is created when you create your own device.

## B. Login the tracking system:


Maybe you will see an alarm window like this:



This is because you haven't any data in the server now.

## C. Create your devices

- Click "Device Status", you will see a button of "New Device" below the window.



Device Name	IMEI	Valid Date	Status	Description	Country	Email	Track Status
Tracker1	356895030021557	2010-04-10/2010-12-10	VALID	PT-10 LC	China	eric@weiom.com	Inaction
WT-9	011691000703788	2010-05-07/2010-06-07	OUT OF BALANCE	20100507	CHINA	ERIC@WEIOM.COM	Inaction
WT-9 HK	011691000703507	2010-05-08/2010-06-08	OUT OF BALANCE	20100508	CHINA	ERIC@WEIOM.COM	Inaction
100531	011691000703663	2010-05-31/2010-07-26	VALID	WT-9	china	eric@weiom.com	Inaction
Eric	356895034143944	2010-06-12/2010-06-30	VALID	VT8			Inaction

- Click this button, and then input information of your new device.




Attention: This password isn't the password that you login as a user but login with this IMEI number.

After you apply your new device, when the status of your device is changed to "Valid", you can use this device for tracking.


## D. Set your tracker

For tracking with GPRS, we need to set right parameters. Connect your tracker and PC with USB cable, then open it; when the USB sign change to green, click the “Start” button in QuickSet function:



Then input parameters in it. If some parameters that you don' t want to change, just let it be blank.

This is an example:




- ✧ “Your cell number”: input your cell phone number, it’ s for timer & SOS.
- ✧ “APN name”: APN name of the SIM card in the tracker. Refer to you SP.
- ✧ “User name” & “Password”: Some APN doesn’ t need the User name & Password, so we haven’ t wrote any thing in this example. Remember it just an example, you must ask your Service Provider (SP) that if your SIM card need the User name & Password to use GPRS.
- ✧ “IP address”: 174.36.139.111
- ✧ “Port” : 12914

After you finished, click “Confirm” button. Wait a few seconds for setting; you will get the successful tips. Then you can disconnect your tracker; put it to balcony or somewhere can find the sky.

## E. Start Tracking

Click “Track Mapping”, you will see a page like this:



Detail of the button:

**Title:**

IMEI  TIMER

SOS  Very SOS

DISTANCE ALARM

OVER SPEED

LOW BATTERY

Memory Full

**Device:**

eric

**From:**

**To:**

**Start View**

**Search**

**Title:** choose the kind of messages that you want display on your Tracking Map;

**Device:** choose the device you want to display on your Tracking Map;

**From, to:** choose the time zone of the point you want to display;

**Start View:** Track your device in real-time;

**Search:** display the point according to the condition that you chose.

## F. Reports



### Detail Reports

Event Title:  IMEI  TIMER  SOS  Very SOS  DISTANCE ALARM!  OVER SPEED  LOW BATTERY  Memory Full

From:

To:

Device Name:  eric

**Search**

**General Report**

No Data

The title of the Reports is same with “Track Mapping”. Select condition and press “Search” button you will see the point accord with the condition what you selected. “General Report” is used to create an Excel table with the data.

## G. User Profile

You can change the user info here.

